

Turbo Switch (Moeller) Wiring Schematic

1. Power cord from wall to 3L2 & 5L3
2. Power cord to motor 4T2 & 6T3
3. 2 1/2" jumper from bottom A2 to 2T1
4. 8" jumper from bottom A2 to green switch n.o.3
5. 2 1/2" jumper from A1 to 5L3
6. 4" jumper from 3L2 to red switch n.c. 2
7. 4" jumper from 3L2 to green switch n.o. 4
8. 5" jumper from 1L1 to red switch n.c. 1
9. Wires from neon light go to A1 & red switch n.c. 2
10. Ground wires to back of box

