

Turbo Switch (Telemecanique) Wiring Schematic

1. Power cord from wall to 3L2 & 5L3
2. Power cord to motor 4T2 & 6T3
3. 2 1/2" jumper from A2 to 2T1
4. 8" jumper from A2 to green switch n.o.3
5. 2 1/2" jumper from A1 to 5L3
6. 4" jumper from 3L2 to red switch n.c.2
7. 4" jumper from 3L2 to green switch n.o.4
8. 5" jumper from 1L1 to red switch n.c.1
9. Wires from l.e.d. light go to A1 & red switch n.c.2
10. Ground wires to back of box

